RESTRICTED

TELECOMMUNICATIONS
Z 880

# SIGNAL GENERATOR NO. I, Mks. I (WY 0063), 2 (WY 0062) and 2\* (WY 0268)

## **DATA SUMMARY**

### **PURPOSE**

To provide an R.F. signal of constant amplitude to an internal accurately calibrated variable attenuator. The output from the attenuator is used in measuring the performance of telecommunications equipment.

## DESCRIPTION

A R.F. oscillator provides a C.W. signal, variable in frequency over a wide range. The output is adjusted during operation to IV R.M.S., by means of a thermocouple monitor, and fed to the variable attenuator, from which any output from  $I_\mu V$  to IV may be taken. A modulator stage allows of internal amplitude modulation at an audio frequency to a known variable depth, if required. Provision is also made for the application of external modulation, either direct or amplified.

### PHYSICAL DATA

Weight :78 lb.

Height; 12 in. Fover projections.


Height: 12| in. Length: 29] in. Width: 10 in.

## FREQUENCY

R.F.: 85kc/s in eight ranges. Internal modulation: 400 cs.

over projections.





Distribution Class 930. Code No. 6

Page 1

# **TELECOMMUNICATIONS**

2 380

## PERFORMANCE

PERFORMANCE Output is continuously variable from  $1\mu V$  to 1V. R.F. accuracy: Below 4.5 Mc, s  $5^{\circ}$ ,  $0.2\mu V$  4.5 to 15 Mc, s  $10^{\circ}$ ,  $0.3\mu V$  15 to 25 Mc s  $20^{\circ}$ ,  $0.5\mu V$  Modulation: depth 0 to  $75^{\circ}$ , Accuracy:  $5^{\circ}$ , Output impedance (Mk. 1): 1 to  $10\mu V$ : 10.8 10 to  $100\mu V$  is 15.8  $100\mu V$  to 1V: 52.5  $100\mu V$  to 1V:  $100\mu V$  in  $100\mu V$  to  $100\mu V$  to  $100\mu V$  in  $100\mu V$  in  $100\mu V$  to  $100\mu V$  in  $100\mu V$  in 52.5 ณ : 152.5 ♀

# POWER REQUIREMENTS AND CONSUMPTION

Mains or battery supply may be used.

Mains: 200 to 250V, 40 to 100 c's, A.C. Consumption: 40W,

Battery: H.T., 200V at 30mA,
L.T., 4V at 3.5A.

# RESTRICTED

ELECTRICAL AND MECHANICAL ENGINEERING REGULATIONS

### **OUTPUT TERMINATION**

The output is taken via a screened coaxial cable terminating in a dummy aerial, which may be put in or out of circuit. The minimum external impedance should be not less than  $200\, {\rm g}$  for outputs of  $1\mu V$  to  $100\, mV$ , and not less than  $1k\, {\rm g}$  for outputs of  $100\, mV$  to 1V.

### **VALVES**

	Mks. I and 2	Mk. 2*	
R.F. oscillator	AC/P	ML4	
A.F. oscillator	AC-P	ML4	
A.F. amplifier	AC P	ML4	
F.W. rectifier	AU3A (UU5 c	AU3A (UU5 or MU12 14)	

END

Issue 1, 1 Jun. 1946

Page 2